

Dr. Bassem Al-Halabi, S&amp;E362

March 6, 2000

Name:

Grade: /10

- [4] 1) For the following program segments, execute each program one instruction at a time. At the end of each instruction execution, indicate any changes in registers and/or memory locations. Note that the results of any instruction may be operands for succeeding instructions.

	D1	D2	A1			
	7172 7374	8182 8384	0000 A006	00A000	55	
				00A001	55	
				00A002	55	
MOVEM.L D1, -(A1)				00A003	55	
				00A004	55	
MOVEM.W (A1)+, D2/D1				00A005	55	
				00A006	55	
				00A007	55	

	D1	D2
	7172 7374	8182 8384
CLR.B D1		
ROL.L #8, D1		
ORI.L #0F0F0F0F, D2		